

# Arcus Motion Control Production Summary

Model	Type	Axis	Motor Size	Driver	Com	Lim/ Home	Pul/Dir In	Alarm In	Enc In	Pul/Dir Out	InPos/ Out	Alarm Out	Enc	DI/DO	AL
<b>PMX Series</b>															
PMX-4ET-SA	C	4	-	-	ETH	x4	-	x4	x4	x4	-	-	-	8/8	-
PMX-4EX-SA	C	4	-	-	USB/485	x4	-	x4	x4	x4	-	-	-	8/8	8
PMX-4CX-SA	C	4	-	-	USB/485	x4	-	-	-	x4	-	-	-	4/4	-
PMX-2EX-SA	C	2	-	-	USB/485	x2	-	-	x2	x2	-	-	-	8/8	2
PMX-2ED-SA	C+D	2	-	2X8MS/1.5A/24V	USB/485	x2	-	-	x2	-	-	-	-	8/8	2
<b>ACE Series</b>															
ACE-SDE	C+D	1	-	500MS/3A/48V	USB/485	x1	-	x1	x1	-	x1	x1	-	6/2	2
ACE-SDX	D	1	-	500MS/3A/48V	DIO	-	x1	-	-	-	-	x1	-	-	-
ACE-SDC-V3	C+D	1	-	16MS/2A/24V	USB/AI/DIO	-	-	-	-	-	-	-	-	6/2	1
ACE-SXE	C	1	-	-	USB/485	x1	-	x1	x1	x1	x1	x1	-	6/2	2
ACE-SXC	C	1	-	-	USB	x1	-	x1	-	x1	-	-	-	3/2	-
<b>DMX Series</b>															
DMX-ETH	M+D+C+E	1	17/23	500MS/3A/48V	ETH	x1	-	-	-	-	-	-	Yes	2/2	-
DMX-UMD	M+D+C+E	1	17/23	500MS/3A/48V	USB/485	x1	-	-	-	-	x1	x1	Yes	6/2	-
DMX-K-SA	M+D+C+E	1	17/23	16MS/2.5A/35V	232/485	x1	-	-	-	-	x1	x1	Yes	6/3	-
DMX-K-SA-11	M+D+C+E	1	11	16MS/1.5A/24V	485	x1	-	-	-	-	-	-	Yes	3/1	-
DMX-J-SA	M+D+C	1	17	16MS/2.0A/24V	USB	x1	-	-	-	-	-	-	-	2/2	-
DMX-A2-DRV	M+D+(E)	1	17/23	500MS/3A/48V	DIO	-	x1	-	-	-	-	x1	Opt	-	-
DMX-K-DRV	M+D	1	11/17/23	16MS/2.5A/24V	DIO	-	x1	-	-	-	-	x1	-	-	-
DMX-K-DRV-34	M+D	1	34	64MS/4.5A/48V	DIO	-	x1	-	-	-	-	x1	-	-	-